# 24V DC | **LED-DR100** Constant Voltage Driver



PROJECT:	TYPE:
LOCATION:	CAT:
THE LEWIS CO. P. S. L. S	The Carlot Marie The Ca

Constant voltage driver in either 12V DC or 24V DC outputs

### **Features**

- 12V or 24V DC constant voltage hardwire driver; 100W capacity
- Non-dimmable on primary side; Utilize secondary side for Trulux™ controls or PWM dimming
- Universal AC input / Full Range
- Protections: Short Circuit / Overload / Over Voltage
- Built-in constant current limiting circuit
- Fully isolated plastic case; Fully encapsulated with IP67 level
- Input via 11" 18AWG conductors
- Output via 11" 14AWG conductors

### Mounting

Set upon flat surface or house in an enclosure

### **Applications**

Suitable for LED lighting

### Warranty

2 years

## Technical Information








Model	LED-DR100-12	LED-DR100-24
Output DC Voltage	12V DC	24V DC
Rated Current	8.5A	4.2A
Maximum Load	100W (non-dimming); 97W (dimming*)	
Minimum Load	20W (non-dimming); 1W (dimming*)	
Input Voltage Range	100-240V AC (2.2A)	
Frequency Range	50/60Hz	
Efficiency	85%	88%
Dimming	Non-dimmable on primary side; Utilize secondary side for Trulux controls or PWM dimming*	
Overload Protect	Hiccup mode, recovers automatically after fault condition is removed	
Over Voltage Protect	Shut down o/p voltage, re-power on to recover	
Operating Temp	-13°F to 158°F (-25°C to 70°C)	
Operating Humidity	20 ~ 90% RH non-condensing	
Rating	cURus for dry and damp locations; RoHS Compliant	

\*Utilize Trulux controller + receiver combo on secondary side (sold separately); PWM dimming will consume ±3W internally

### **Dimensions**



# Ordering Information




### LED-DR100-12 includes:

(1) 12V DC Constant Voltage Power Supply

### LED-DR100-24 includes:

(1) 24V DC Constant Voltage Power Supply

Example Part # LED-DR100-12





# Additional Information

# ■ Static Characteristics | Static Characteristics | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 |

# **NOTES**